

**Article No.:** 6SL3220-1YE40-0UF0

Client order no. : Order no. : Offer no. : Remarks :

Item no.:

**Rated data** 

Input		
Number of phases	3 AC	
Line voltage	380 480 V +	10 % -20 %
Line frequency	47 63 Hz	
Rated voltage	400V IEC	480V NEC
Rated current (LO)	104.00 A	91.00 A
Rated current (HO)	94.00 A	80.00 A

## Output

Number of phases 3 AC	
Rated voltage 400V IEC 480V NEC <sub>1</sub>	
Rated power (LO) 55.00 kW 75.00 hp	
Rated power (HO) 45.00 kW 60.00 hp	
Rated current (LO) 110.00 A 96.00 A	
Rated current (HO) 90.00 A 77.00 A	
Rated current (IN) 113.00 A	
Max. output current 149.00 A	
Pulse frequency 4 kHz	
Output frequency for vector control 0 200 Hz	
Output frequency for V/f control 0 550 Hz	

## **Overload capability**

-	Low Overload (LO)
	110% base load current IL for 60 s in a 300 s cycle time
	High Overload (HO)

150% x base load current IH for 60 s within a 600 s cycle time

General tech. specifications	
Power factor λ	0.90 0.95
Offset factor cos φ	0.99
Efficiency η	0.97
Sound pressure level (1m)	70 dB
Power loss <sub>3)</sub>	1.730 kW
Filter class (integrated)	Unfiltered
EMC category (with accessories)	without



Consignment no. : Project :

Aiiib	ient conditions
Standard board coating type	Class 3C2, according to IEC 60721-3-3 2002
Cooling	Air cooling using an integrated fan
Cooling air requirement	0.083 m³/s (2.931 ft³/s)
Installation altitude	1,000 m (3,280.84 ft)
Ambient temperature	
Operation	-20 45 °C (-4 113 °F)
Transport	-40 70 °C (-40 158 °F)
Storage	-25 55 °C (-13 131 °F)
Relative humidity	
Max. operation	95 % At 40 °C (104 °F), condensation and icing not permissible
Me	chanical data
Degree of protection	IP20 / UL open type
Size	FSE
Net weight	27 kg (59.52 lb)
Dimensions	
Width	275 mm (10.83 in)
Height	551 mm (21.69 in)
Depth	248 mm (9.76 in)



## Article No.: 6SL3220-1YE40-0UF0


Inputs / outputs		
Standard digital inputs		
Number	_	
Switching level: 0 → 1	6 11 V	
Switching level: 1 → 0	5 V	
Max. inrush current	15 mA	
	13 IIIA	
ail-safe digital inputs		
Number  Digital outputs		
Number as relay changeover contact 2Output (resistive load)		
20 a.p.a. (100.10a.vo 10a.a.)	DC 30 V, 5.0 A	
Number as transistor		
Analog / digital inputs		
Number	2 (Differential input)	
Resolution	10 bit	
	10 Dit	
Switching threshold as digital input		
0 → 1	4 V	
1 → 0	1.6 V	
Analog outputs		
Number	1 (Non-isolated output)	
PTC/ KTY interface		
1 motor temperature sensor input, sen and Thermo-Click, accuracy ±5 °C	sors that can be connected: PTC, KTY	
Closed-loop co	ontrol techniques	
//f linear / square-law / parameterizable	•	
//f with flux current control (FCC)	Yes	
//f ECO linear / square-law	Yes	
Sensorless vector control	Yes	
/ector control, with sensor	No	
,		
Encoderless torque control	Yes	
Torque control, with encoder	No	

Communication

Communication

	onnections	
Signal cable		
Conductor cross-section	0.15 1.50 mm² (AWG 24 AWG 16)	
Line side		
Version	screw-type terminal	
Conductor cross-section	25.00 70.00 mm <sup>2</sup> (AWG 6 AWG 3/0)	
Motor end		
Version	Screw-type terminals	
Conductor cross-section	25.00 70.00 mm <sup>2</sup> (AWG 6 AWG 3/0)	
DC link (for braking resistor)		
PE connection	Screw-type terminals	
Max. motor cable length		
Shielded	200 m (656.17 ft)	
Unshielded	300 m (984.25 ft)	

Converter losses to IEC61800-9-2*	
Efficiency class	IE2
Comparison with the reference converter (90% / 100%)	47.9 %



The percentage values show the losses in relation to the rated apparent power of the converter.

The diagram shows the losses for the points (as per standard IEC61800-9-2) of the relative torque generating current (I) over the relative motor stator frequency(f). The values are valid for the basic version of the converter without options/components.

\*converted values

Standards		
Compliance with standards	UL, cUL, CE, C-Tick (RCM), EAC, KCC, SEMI F47, REACH	
CE marking	EMC Directive 2004/108/EC, Low- Voltage Directive 2006/95/EC	

PROFINET, EtherNet/IF

<sup>1)</sup> The output current and HP ratings are valid for the voltage range 440V-480V

<sup>3)</sup> Typical value. More information can be found in the element group "Converter losses to IEC 61800-9-2" in this datasheet.