

1

2

3

4

REV. ECN NO.

ENCODER CONNECTOR
AMP 1-172169-9MOTOR CONNECTOR
CP-01106011

A

A

B

B

(52.75)

LE±50

LP±50

LR

5

3

2.5

LS

LW

φS6

A

φ30h7

A

φ0.04

A

0.02

A

0.04


A

LL


2-φ4.5
PCD φ46OIL-SEAL(TC TYPE)
ONLY FOR OIL-SEAL MODEL

DIMENSION TABLE (MODEL WITH BRAKE)

MODEL	LL	LR	LS	S	LW	WK	W	T	RH	TP	LP	LE
ECMA-C□0401BS	136.6	25	20	8	—	—	—	—	—	M3, Depth 8	300	300
ECMA-C□0401DS					16	3	3	3	6.2	—		
ECMA-C□0401FS					16	3	3	3	6.2	M3, Depth 8		
ECMA-C□0401HS					16	3	3	3	6.2	M3, Depth 8		



SHAFT END DETAILS



KEY DETAILS

C

C

Pobrano z: <https://automatyka-sklep.eu/serwosilnik-z-hamulcem-delta-electronics-0-32nm-100w-3000-obrmin-ecma-c10401bs>

2

3

4

台灣電子工業股份有限公司 DELTA ELECTRONICS, INC.		DRAWN:	DESIGN:
APPROVE:		DATE: 10/21/2013	
THESE DRAWINGS AND SPECIFICATIONS ARE THE PROPERTY OF DELTA ELECTRONICS, INC. AND SHALL NOT BE REPRODUCED OR USED AS THE BASIS FOR THE MANUFACTURE OR SELL OF APPARATUS OR DEVICES WITHOUT PERMISSION.			
DIMENSIONAL TOLERANCES DECIMALS <50 ±0.1 <50 ±0.15 <50 ±0.2 <30° ±0.1° X ±0.3 >50-100 ±0.15 >50-100 ±0.2 >50-100 ±0.25 >30°-60° ±0.3° X.X ±0.2 >100-200 ±0.2 >100-200 ±0.25 >100-200 ±0.3 >60°-90° ±0.5° X.XX ±0.1 >200 ±0.2 >200 ±0.25 >200 ±0.3			
DESCRIPTION: CONFIDENTIAL MOTOR_F40_BRAKE		PART NO.: REV. 00	
USED ON	UNIT	mm	SHEET 1 OF 1