

1

2

3

4

REV. ECN NO.

ENCODER CONNECTOR
AMP 1-172169-9MOTOR CONNECTOR
CP-01106011

LE±50

LP±50

LR

LS

LW

ØSh6

Ø50h7

Ø0.04

A

0.02


0.04

A


OIL-SEAL(TC TYPE)
ONLY FOR OIL-SEAL MODEL

DIMENSION TABLE (MODEL WITH BRAKE)

MODEL	LL	LR	LS	S	LW	WK	W	T	RH	TP	LP	LE
ECMA-JC0604SS	166.8	30	27	14	20	5	5	5	11.0	M4, Depth 15	300	300



SHAFT END DETAILS



KEY DETAILS

Pobrano z: <https://automatyka-sklep.eu/serwosilnik-z-hamulcem-delta-electronics-1-27nm-400w-3000-obrmin-ecma-j10604ss>

 台達電子工業股份有限公司 DELTA ELECTRONICS, INC.	DRAWN:	DESIGN:																																												
	APPROVE:	DATE: 10/21/2013																																												
THESE DRAWINGS AND SPECIFICATIONS ARE THE PROPERTY OF DELTA ELECTRONICS, INC. AND SHALL NOT BE REPRODUCED OR USED AS THE BASIS FOR THE MANUFACTURE OR SELL OF APPARATUS OR DEVICES WITHOUT PERMISSION.	DIMENSIONAL TOLERANCES																																													
	<table><tr><th></th><th>()</th><th>()</th><th>()</th><th>()</th><th>ANGLES</th></tr><tr><th>DECIMALS</th><td><50</td><td>±0.1</td><td><50</td><td>±0.15</td><td><50</td><td>±0.2</td><td><30°</td><td>±0.1°</td></tr><tr><th>X</th><td>±0.3</td><td>>50~100</td><td>±0.15</td><td>>50~100</td><td>±0.2</td><td>>50~100</td><td>±0.25</td><td>>30°~60°</td><td>±0.3°</td></tr><tr><th>X.X</th><td>±0.2</td><td>>100~200</td><td>±0.2</td><td>>100~200</td><td>±0.25</td><td>>100~200</td><td>±0.3</td><td>>60°~90°</td><td>±0.5°</td></tr><tr><th>X.XX</th><td>±0.1</td><td>>200~</td><td>±0.2</td><td>>200~</td><td>±0.25</td><td>>200~</td><td>±0.3</td><td>>200~</td><td>±0.3°</td></tr></table>			()	()	()	()	ANGLES	DECIMALS	<50	±0.1	<50	±0.15	<50	±0.2	<30°	±0.1°	X	±0.3	>50~100	±0.15	>50~100	±0.2	>50~100	±0.25	>30°~60°	±0.3°	X.X	±0.2	>100~200	±0.2	>100~200	±0.25	>100~200	±0.3	>60°~90°	±0.5°	X.XX	±0.1	>200~	±0.2	>200~	±0.25	>200~	±0.3	>200~
	()	()	()	()	ANGLES																																									
DECIMALS	<50	±0.1	<50	±0.15	<50	±0.2	<30°	±0.1°																																						
X	±0.3	>50~100	±0.15	>50~100	±0.2	>50~100	±0.25	>30°~60°	±0.3°																																					
X.X	±0.2	>100~200	±0.2	>100~200	±0.25	>100~200	±0.3	>60°~90°	±0.5°																																					
X.XX	±0.1	>200~	±0.2	>200~	±0.25	>200~	±0.3	>200~	±0.3°																																					
DESCRIPTION: MOTOR_F60_BRAKE_380V	PART NO.:																																													
	REV.:																																													
USED ON	UNIT	SHEET 1 OF 1																																												